

Velociti® Series 3 Detectors

Photoelectric Detectors

Description

The Gamewell-FCI, Velociti® Series 3 intelligent photoelectric detectors with integral communication provide point location for alarm communication and selective maintenance. Designed in a modern bright white color, the Velociti Series 3 is aesthetically pleasing for today's contemporary buildings.

The Velociti Series 3 smoke detectors are intelligent addressable detectors with point ID capability that enable each detector address to be set with rotary address switches providing exact device locations. The photoelectric detector continually monitors the detected temperature and reports it to the fire alarm control panel. The modern design and expanded color options support a variety of contemporary aesthetic demands. In addition, each detector is constructed for exceptional installation and maintenance efficiency.

The Gamewell-FCI, ASD-PL3 photoelectric detector's re-designed optical sensing chamber is engineered to sense smoke produced by a wide range of combustion sources in accordance with more stringent code standards. The sensitivity of Velociti series detectors can be programmed using the control panel software to suit the environment. The ASD-PL3R photoelectric detector is also remote test capable that may be used with a DNR (DNRW) duct smoke detector housing. The ASD-PTL3 multi-sensor detector offers either photoelectric detection or thermal detection through dual electronic thermistors at 135°F fixed temperature thermal sensing.

For legacy installations, service detectors are available in the classic ivory color that will operate in both Velociti and CLIP protocol for backwards compatibility. Service models are designated by the -IV part number after the detector model.

Note: Although the E3 Series® and S3 Series panels support both the Velociti® and CLIP™ protocols, the GWF-7075 panel does not support the CLIP protocol. To obtain a complete list of panels that are listed to Velociti Series 3 detectors, refer to the Compatibility Addendum for Gamewell-FCI Manuals, P/N:9000-0427-L8.



Photoelectric Detector

FEATURES & BENEFITS

- Complies with UL® Standard 268 7th Edition
- Designed with a new profile to offer modern and improved aesthetics
- Contains a built-in functional test switch activated by external magnet
- Supports a low standby current
- Provides rotary address switches (01-159)
- Supplies optional relay, isolator, or sounder bases (standard or low frequency)
- Includes dual LEDs for 360° visibility
- Offers expanded color options

Ordering Information

NOTE: "-IV" suffix indicates Ivory color model.

NOTE: "-BL" suffix indicates Black color model.

NOTE: "WH" suffix indicates Bright White color model.

ASD-PL3: Photoelectric smoke detector, bright white, Velociti

ASD-PL3R: Photoelectric smoke detector, remote test capable, for use with DNR(W) duct smoke detectors, bright white, Velociti

ASD-PTL3: Photoelectric smoke detector with thermal sensing, bright white, Velociti

ASD-PL3-IV : Photoelectric smoke detector, ivory, Velociti/CLIP

ASD-PL3R-IV: Photoelectric smoke detector, remote test capable, for use with DNR(W) duct smoke detectors, ivory, Velociti/CLIP

ASD-PTL3-IV : Photoelectric smoke detector with thermal sensing, ivory, Velociti/CLIP

Intelligent Bases

For details on intelligent bases, refer to Data Sheet P/N: 9021-60540.

Note: "IV" suffix indicates Flashscan and CLIP devices. "WH" suffix indicates bright white

B501-WHITE: 4" Flangeless mounting base, bright white

B501-WHITE-BP: 4" Flangeless mounting base bulk pack, bright white

B501-IV: 4" Flangeless mounting base, ivory

B300-6: 6" Flanged mounting base, bright white

B300-6-IV: 6" Flanged mounting base, ivory

B300-6-BP: 6" Flanged mounting base bulk (Pack of 10)

B200SR-WH: Standard sounder base, bright white

B200SR-IV: Standard sounder base, ivory

B200S-WH: Intelligent addressable sounder base, bright white

B200S-IV: Intelligent addressable sounder base, ivory

B200SR-LF-WH: Standard low frequency sounder base, bright white

B200SR-LF-IV: Standard low frequency sounder base, ivory

B200S-LF-WH: Intelligent addressable low frequency sounder base, bright white

B200S-LF-IV: Intelligent addressable low frequency sounder base, ivory

B224RB-WH: Relay base, bright white

B224RB-IV: Relay base, ivory

B224BI-WH: Isolator base, bright white

B224BI-IV: Isolator base, ivory

DNR: Intelligent duct detector housing, non-relay

DNRW: Intelligent duct detector housing, non-relay, watertight

Ordering Information

Accessories

SMB600: Surface Mounting Kit (flanged)

TR300: Accessory Flange Ring for B300 6" Base, bright white

TR300-IV: Accessory Flange Ring for B300 6" Base, ivory

RA100Z: Remote LED annunciator, 3-32 VDC

The annunciator mounts to a U.S. single-gang electrical box. For use with B501 and B300-6.

CK300: Bright White detector kit (Pack of 10)

CK300-IR: White, detector color kit for use with MCS-COF Series Detectors. (Pack of 10)

CK300-IV: Ivory, detector color kit. (Pack of 10)

CK300-IR-IV: Ivory, detector color kit for use with MCS-COF Series detectors. (Pack of 10)

CK300-BL: Black detector kit. (Pack of 10)

CK300-IR-BI: Black, detector color kit for use with MCS-COF Series detectors. (Pack of 10)

M02-04-01: Detector test magnet.

M02-09-00: Test magnet with telescoping handle.

XR2B: Detector removal tool. Allows the installation and/or removal of the detector heads from the bases in high ceiling applications.

XP-4: Extension pole for XR2B. Shipped with three, 5-foot (1.524,m) sections.

Velociti® Series 3 Detectors Technical Specifications

SYSTEMS

Photoelectric Intelligent Detector:

Physical Specifications

Height: 2.0 inches (51 mm) installed in B300-6 base

Diameter:

6.1 inches (15.49 cm) installed in B300-6 base

4 inches (10.16 cm) installed in B501 base

Shipping Weight: 3.4 oz (96.4 g)

Operating Temperature Range:

Photo: 32° F to 122° F (0° C to 50° C)

Photo in Duct Applications: -4° F to 158° F
(-20° C to 70° C)

Photo with Thermal: 32° F to 100° F (0° C to 38° C)

Operating Humidity Range: 10% to 93%
non-condensing

Rate-of-Rise Detection: Responds to greater than
15°F/minute or 135°F (8.3° C/minute or 57°C)

Air Velocity Range: 0 to 4,000 ft/min
(0 to 1219.2 m/min)

Electrical Specifications

Voltage Range: 15 to 32 VDC

Standby Current (@ 24 VDC): 200 UA (one
communication every 5 seconds with green LED
enabled)

Max Alarm Current (max.): 2 mA @ 24 VDC (one
communication every 5 seconds with red LED
enabled)

Max Current (max.): 4.5 mA @ 24 VDC (one
communication every 5 seconds with amber LED
enabled)

Isolator Load Rating: 0.0063

STANDARDS

The Velociti® Series 3 Photoelectric Detectors are designed to comply with the following standard:

UL Standard: UL 268

AGENCY LISTINGS AND APPROVALS

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

UL: S2332

FM: 3023594

MEA FDNY: COA-219-02-E Vol. VI

CSFM: 7272-1703:0501

ISO 9001 Certification

For a complete listing of all compliance approvals and certifications, please visit:
<http://www.gamewell-fci.com/en-US/documentation/Pages/Listings.aspx>

E3 Series®, Velociti® and Gamewell-FCI® are registered trademarks of Honeywell International Inc.

UL® is a registered trademark of Underwriter's Laboratories Inc.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For more information

Learn more about Gamewell-FCI's Velociti® Series 3 Detectors and other products available by visiting www.Gamewell-FCI.com

Honeywell Gamewell-FCI

12 Clintonville Road
Northford, CT 06472-1610
203.484.7161
www.honeywell.com

9020-0617 | K | 04/2018
©2018 Honeywell International Inc.

Honeywell