

AMM-2F

Addressable Monitor Module

General

The Gamewell-FCI Velociti® Series, addressable monitor module AMM-2F is a single Style B, Class B initiating device circuit (IDC) with a 47KW end-of-line resistor. This module provides an address for any device or group of devices connected to this circuit on the signaling line circuit (SLC) of the Gamewell-FCI addressable series fire alarm control panel. Any initiating device with normally open (N.O.) dry contacts may be made addressable when connected to the AMM-2F module.

The Velociti® Series use a communication protocol that substantially increases the speed of communication between the sensors and certain Gamewell-FCI analog addressable fire alarm controls. These devices operate in a grouped fashion. If one of the devices in the group has a status change, the panel's microprocessor stops the group poll and concentrates on the single device. The net effect is response speed up to five times greater than earlier designs.

The AMM-2F module can be programmed to provide a wide variety of input functions to the Gamewell-FCI addressable series fire alarm control panels. It can be identified as a manual station, heat detector, plenum detector, waterflow switch, tamper switch, N.O. contact, smoke detector, projected beam smoke detector, sub loop, remote zone, etc. It can also serve as a remote system silence, system reset, system acknowledge or drill switch. It is even possible to customize its device type to meet specific job requirements.

The initiating device circuit of the AMM-2F can support a maximum line resistance of up to 40 ohms allowing the use of linear heat detection devices. The compact size facilitates the installation of the module inside manual stations, or mounting boxes of various types of alarm initiating devices.

Ordering Information

AMM-2F: Addressable monitor module, single circuit, Style B, Class B



AMM-2F

FEATURES & BENEFITS

- Compact size allows easy installation
- Class B, Style B, initiating circuit
- 40 Ohm line resistance for each initiating device circuit
- Connects to any normally open dry contact device

AMM-2F Technical Specifications

System

Supervisory Current: .000375 amps

Alarm Current: .00060 amps

Operating Temperature: 32° to 120° F (0° to 49° C)

Relative Humidity: 10 to 93% (non-condensing)

End-of-Line Resistance: 47K ohms

Dimensions: 1.3" L x 2.5" W x 0.5" D
(3.3 x 6.4 x 1.3 cm)

TEMPERATURE AND HUMIDITY RANGES

This system meets NFPA requirements for operation at 0 – 49°C/32 – 120°F and at a relative humidity 93% ± 2% RH (noncondensing) at 32°C ± 2°C (90°F ± 3°F).

However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and its peripherals be installed in an environment with a normal room temperature of 15 – 27°C/60 – 80°F.

STANDARDS

The E3 Series Control Panel is designed to comply with the following standard:

UL Standard: UL 864 9th Edition

AGENCY LISTINGS AND APPROVALS

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

UL: S1949

FM: 3023594

MEA FDNY: 227-03-E VOL. IV

CSFM: 7300-1703:0102

ISO 9001 Certification

For a complete listing of all compliance approvals and certifications, please visit: <http://www.gamewell-fci.com/en-US/documentation/Pages/Listings.aspx>

Velociti® and Gamewell-FCI® are registered trademarks of Honeywell International Inc. UL® is a registered trademark of Underwriters Laboratories Inc.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For more information

Learn more about Gamewell-FCI's AMM-2F and other products available by visiting www.Gamewell-FCI.com

Honeywell Gamewell-FCI

12 Clintonville Road
Northford, CT 06472-1610
203.484.7161
www.honeywell.com

9020-0626 | F | 11/17
©2017 Honeywell International Inc.

Honeywell